

ACM Series Power Supply/Chargers with Multi-Output Access Power Controllers

Description

Altronix ACM series distribute and switch power to access control systems and accessories. They convert a 115VAC 60Hz input into eight (8) independently controlled 12VDC or 24VDC fuse protected outputs. These power outputs can be converted to dry form "C" contacts. Outputs are activated by an open collector sink or normally open (NO) dry trigger input from an Access Control System, Card Reader, Keypad, Push Button, PIR, etc. Units will route power to a variety of access control hardware devices including: Mag Locks, Electric Strikes, Magnetic Door Holders, etc. Outputs will operate in both Fail-Safe and/or Fail-Secure modes. The FACP Interface enables Emergency Egress, Alarm Monitoring, or may be used to trigger other auxiliary devices. The fire alarm disconnect feature is individually selectable for any or all of the eight (8) outputs.



Key Features

| Eight (8) independently controlled outputs. Output options: | - Fire Alarm disconnect (latching or non-latching) is individually selectable for any or all of the eight (8) outputs. |
|--|--|
| a) Eight (8) Fail-Safe and/or Fail-Secure power outputs; | - Alarm output relay indicates that FACP input is triggered |
| b) Eight (8) form "C" 5A rated relay outputs;c) Any combination of the above. | - Fire Alarm disconnect input options: a) Normally open (NO) or normally closed (NC) dry contact input |
| - Eight (8) auxiliary power outputs (unswitched). | b) Polarity reversal input from FACP signaling circuit. |
| - Output fuses are rated @ 3.5A. | - Built-in charger for sealed lead acid or gel type batteries. |
| - Filtered and electronically regulated outputs. | - Instantaneous transfer to stand-by batteries. |
| - Supervision: | - UL Listed in the U.S. and Canada. |
| - AC Fail - Battery Fail and Battery Presence. | - Lifetime Warranty / Made in the U.S.A. |

ACM Series Power Supply Configuration Reference Chart

| Altronix Model Number | 12VDC Total Output Current | 24VDC Total Output Current | Fused Outputs | Individual Output Rating | 115VAC 60Hz Input Current Draw | Power Supply Board Input Fuse Rating | Power Supply Board Battery Fuse Rating |
|--------------------------|----------------------------------|----------------------------------|------------------|--------------------------------|--------------------------------------|--|--|
| AL400ULACM | - 4A | ЗА | 8 | 3.5A | 3.5A | 5A/250V | 15A/32V |
| AL400ULACMJ | | | | | | | |
| AL600ULACM | - 6A | 6A | | | 3.5A | | |
| AL600ULACMJ | | | | | | | |
| AL1012ULACM | 104 | _ | | | 2.6A | | 154/001/ |
| AL1012ULACMJ | - 10A | | | | | | |
| AL1024ULACM | | 10A | | | 4.2A | 6.3A/250V | 15A/32V |
| AL1024ULACMJ | 1 — | | | | | | |

ACM Series Power Supply/Chargers with Multi-Output Access Power Controllers



| Specifications | 3 | | | | | |
|--------------------------------|---|--|------------------------------|---------------------|--|--|
| Input | | Agency Listings | | | | |
| Voltage | 115VAC, 60Hz. | All Models: | | | | |
| Fusing | Varies, see Reference Chart. | Access Control | | UL294 | | |
| - | | Signal Equipme | ent | CSA Standard C22 | | |
| Outputs | | 5 11 | | No.205-M1983 | | |
| Voltage | 12VDC or 24VDC, see Reference Chart. | AL400ULACM(J), AL600ULACM(J) only: | | | | |
| Current | Varies, depending on the model. | California State Fire Marshall Approved | | | | |
| Protection | Fused 3.5A. | | | | | |
| Auxiliary | 3.5A (unswitched). | Physical and Environmental | | | | |
| Other | Overvoltage protection. | Dimensions (H \times W \times D) | | | | |
| | Filtered and regulated outputs. | AL400ULACM, AL600ULACM, AL1012ULACM, | | | | |
| | | and AL1024ULACM: | | | | |
| Back-up Battery (not included) | | 15.5" x 12" x 4.5" (393.7mm x 304.8mm x 114.3mm). | | | | |
| Capacity | 12AH / 12VDC (1 or 2 within enclosure). | AL400ULACMJ, AL600ULACMJ, AL1012ULACMJ, | | | | |
| | 18AH / 12VDC (requires larger "J" enclosure). | and AL1024ULACMJ: | | | | |
| _ | 40 AH / 65 AH (requires separate enclosure). | 18" x 14.5" x 4.625" (457.2mm x 368.3mm x 117.48mm). | | | | |
| Туре | Sealed lead acid or gel type. | Product Weight / Shipping (approx.) | | | | |
| Fuse Rating | 15A @ 32VDC | Model | Product Weight | Shipping Weigh | | |
| | AL600ULACM(J) does not have a battery fuse. | AL400ULACM | 10.7 lbs. (4.85 kg) | 12 lbs. (5.44 kg) | | |
| Failover | Upon AC loss, instantaneous. | AL400ULACMJ | 14 lbs. (6.35 kg) | 15 lbs. (6.8 kg) | | |
| | | AL600ULACM | 10.3 lbs. (4.67 kg) | 11.6 lbs. (5.26 kg | | |
| Fire Alarm Disco | nnect | AL600ULACMJ | 14.85 lbs. (6.74 kg) | 17.1 lbs. (7.76 kg | | |
| Supervised | Latching or non-latching, individually | AL1012ULACM | 10.7 lbs. (4.85 kg) | 12 lbs. (5.44 kg) | | |
| | selectable for any or all of the eight (8) outputs. | AL1012ULACMJ | 14.1 lbs. (6.40 kg) | 15 lbs. (6.80 kg) | | |
| EOL | 10K Resistor. | AL1024ULACM | 11.75 lbs. (5.33 kg) | 13.05 lbs. (5.92 kg | | |
| | | AL1024ULACMJ | 14.9 lbs. (6.76 kg) | 16.1 lbs. (7.3 kg) | | |
| Supervision | | Temperature | | | | |
| AC Failure | Form "C" contacts. | Operating | 0°C to 49°C (32°F to 120°F). | | | |
| Battery | Form "C" contacts. | Storage -20°C to 70°C (-4°F to 158°F). | | | | |
| | | Relative Humid | ity 85% +/-5%. | | | |
| Indicators (LED) | | BTU/Hr (12VDC | C/24VDC): | | | |
| Input | 115VAC is present. | Model | 12VDC | 24VDC | | |
| DC Output | Powered. | AL400ULACM(J) | 24.57 | 36.85 | | |
| Battery | Discharged or not connected. | AL600ULACM(J) | 36.85 | 73.70 | | |
| Relays | Individual LEDs indicate outputs are | AL1012ULACM(J) | 61.42 | N/A | | |
| - | triggered (relays energized). | AL1024ULACM(J) | N/A | 122.84 | | |