

## Miniature 2-Channel RF Receiver & Transmitters

### SK-910RAV2Q 2-Channel Receiver – Transistor Group O/P

- Four programmable output modes:
  - 4-Second Momentary Output
  - Toggle Output
  - Validity Output
  - 1-Second Momentary Output
- Flexible operating voltage: 3~13.8 VDC.
- Up to 500ft (152m) range\*.
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote.
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP).
- Two LEDs indicate RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode.



### SK-919TD2A-UP Factory Pre-Coded Transmitter

### SK-917T2A-U CODEBUMP Transmitter

- Operates up to 500ft (152m), 315MHz\*.
- LED transmission indicator.
- Includes 12VDC alkaline battery.
- Two buttons, three channels.
- SK-919TD2A-UP: Over 68 billion possible codes.
- SK-917T2A-U: 18 quintillion possible codes.

1 1/4" X 2 1/4" X 1 1/2"  
(32x63x38 mm)



2 13/16" X 3 1/2" X 1/2"  
(71x89x13 mm)



### SK-919TP2H-NU Two-Button Handheld Transmitter

- Operates up to 500ft (152m), 315MHz\*.
- Over 68 billion (6.8x10<sup>10</sup>) possible codes.
- Includes two 3VDC lithium batteries.
- Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SK-9HBC).
- Two buttons, three channels.
- Slimline design.

### SK-910RAV2Q Specifications:

Range	Up to 500' (150m) in open air
Operating voltage	3-13.8 VDC
Current Draw	5mA Standby, 15mA LED flashing @ 12 VDC
Output Mode	Programmable 4s momentary (default), 1s momentary, toggle (ON/OFF), validity
# of outputs	2
Output Type	3A Transistor GND
Transmitter	Compatible with all SECO-LARM transmitters

\*Actual range may vary greatly depending on the installation and operating environment.